

**Surface Mount Schottky Barrier Rectifier**
**Reverse Voltage - 20 to 200 V**
**Forward Current - 8 A**
**FEATURES**


- ◆ Metal silicon junction, majority carrier conduction
- ◆ For surface mounted applications
- ◆ Low power loss, high efficiency
- ◆ High forward surge current capability
- ◆ For use in low voltage, high frequency inverters, free wheeling, and polarity protection applications
- ◆ Lead free in comply with EU RoHS 2011/65/EU directives

**MECHANICAL DATA**

- ◆ Case: DO-214AA/SMB
- ◆ Terminals: Solderable per MIL-STD-750, Method 2026
- ◆ Approx. Weight: 0.095g / 0.003oz

**Absolute Maximum Ratings and Electrical characteristics**

Ratings at 25 ° ambient temperature unless otherwise specified. Single phase, half wave, 60Hz resistive or inductive load, for capacitive load, derate by 20 %




Parameter	Symbols	SS82B	SS84B	SS86B	SS88B	SS810B	SS812B	SS815B	SS820B	Units								
Maximum Repetitive Peak Reverse Voltage	<b>V<sub>RRM</sub></b>	20	40	60	80	100	120	150	200	<b>V</b>								
Maximum RMS voltage	<b>V<sub>RMS</sub></b>	14	28	42	56	70	84	105	140	<b>V</b>								
Maximum DC Blocking Voltage	<b>V<sub>DC</sub></b>	20	40	60	80	100	120	150	200	<b>V</b>								
Maximum Average Forward Rectified Current	<b>I<sub>F(AV)</sub></b>	8.0								<b>A</b>								
Peak Forward Surge Current, 8.3ms Single Half Sine-Wave Superimposed On Rated Load (JEDEC method)	<b>I<sub>FSM</sub></b>	170								<b>A</b>								
Maximum Instantaneous Forward Voltage at 8 A	<b>V<sub>F</sub></b>	0.55		0.70		0.85		0.90		<b>V</b>								
Maximum Instantaneous Reverse Current <small>T<sub>A</sub> = 25°C at Rated DC Reverse Voltage T<sub>A</sub> = 100°C</small>	<b>I<sub>R</sub></b>	1.0 50		0.3 25						<b>mA</b>								
Typical Junction Capacitance <sup>(1)</sup>	<b>C<sub>j</sub></b>	650		420						<b>pF</b>								
Typical Thermal Resistance <sup>(2)</sup>	<b>R<sub>θJA</sub></b>	10								<b>°C/W</b>								
Operating Junction Temperature Range	<b>T<sub>j</sub></b>	-55 ~ +150								<b>°C</b>								
Storage Temperature Range	<b>T<sub>stg</sub></b>	-55 ~ +150								<b>°C</b>								


(1) Measured at 1 MHz and applied reverse voltage of 4 V D.C

(2) P.C.B. mounted with 2.0" X 2.0" (5 X 5 cm) copper pad areas.


**Fig.1 Forward Current Derating Curve**




**Fig.2 Typical Reverse Characteristics**




**Fig.3 Typical Forward Characteristic**




**Fig.4 Typical Junction Capacitance**




**Fig.5 Maximum Non-Repetitive Peak Forward Surge Current**



**Fig.6- Typical Transient Thermal Impedance**



**Marking Diagram**



**Ordering information**


Package	Packing Description	Packing Quantity			
DO-214AA SMB	Tape/Reel, 13" reel	3000PCS/Reel 30000PCS/Carton			

**Package Dimensions**

**DO-214AA SMB**

Dim.	Millimeter(mm)		mil	
	Min.	Max.	Min.	Max.
A	2.13	2.44	84	96
E	4.06	4.70	160	185
D	3.3	3.94	130	155
E <sub>1</sub>	5.08	5.59	200	220
A <sub>1</sub>	0.05	0.20	2.0	7.9
L	0.8	1.5	32	59
C	0.152	0.305	6	12
b	1.9	2.2	75	87

The recommended mounting pad size



Unit :  $\frac{\text{mm}}{(\text{mil})}$

## Disclaimer

The information presented in this document is for reference only. GuangDong Youfeng Microelectronics Co.,Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise. The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices). YFW or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale. This publication supersedes & replaces all information previously supplied. For additional information, please visit our website <https://www.yfwdiode.com>, or consult YFW sales office for further assistance.